



- ⌚ Allows control and monitoring of multiple UPSs through RJ-45 ethernet port
- ⌚ Built-in web server
- ⌚ Real-time dynamic graphs of UPS data (voltage, frequency, load level, battery level)
- ⌚ Warning notifications via audible alarm, broadcast, mobile messenger, e-mail and SNMP traps
- ⌚ Historic data log stored in centralized PC database
- ⌚ Simple firmware upgrade with one click
- ⌚ Password security protection and remote access management
- ⌚ Supports optional environmental monitoring detector for temperature, humidity and smoke

**SNMP Web Manager** is a configuration wizard to configure SNMP web card/box in computer with Windows, Linux or MAC OS. If integrated into an NMS web manager :

it can monitor and remote access all distributed SNMP web card in a LAN or INTERNET.

it can not only prevent data loss from power outage and safely shutdown systems, but also store programming data and scheduled shut down the UPSs.

All UPS warnings and fault event records can be kept in SNMP web card.

For more information about available software packages ( Element Manager or Newtork Manager ), please mail us @ sales@powermeitaly.it

Model	SNMP Web Card
Protocol Support	TCP/IP, UDP,SNTP, HTTP, DHCP, SNMP v1/2/3,SMTP
UPS Slot Type	Golden Finger
Network Support	RJ45 10/100BaseT
Supported MIB	RFC1213, RFC1628, Vendor MIB
Supported OS	Windows family, Linux and MAC
Supported Extension Devices	Optional environmental monitoring detector
Power Consumption	3 watt (max.)
Operating Temperature	0 ~ 55°C
Operating Humidity	0% ~ 95%
PHYSICAL	
Dimension, D x W x H (mm)	80 x 26 x 52
Net Weight (kgs)	Approx. 0,1 kgs

Notice : Technical specifications may change without pre-adviced.

